



Table 40 : LFWL, MLFWL Series Dimensions Table

Standard Non-Rust	Major Dimensions (mm)											Number of Ball Circuits	Model No. of Linear Bearing	Weight (kgf)	Basic Load Ratings		
	d	D _{be}	D _o	L	l	D _r	D _p	K	t	t _o	S				C	C _o	
LFWL16 MLFWL16	16	0 -0.009	42	41	150	75	72	58	58	18	20	φ7	5	L16-U×2 ML16-U×2	0.58	92	152
LFWL20A MLFWL20A	20		48	47	150	75	78	64	62	20	22	φ7	5	L20-U×2 ML20-U×2	0.73	104	206
LFWL20B MLFWL20B					200	100									0.91		
LFWL25A MLFWL25A	25	0 -0.010	58	57	200	100	90	76	72	22	30	φ7	6	L25B-U×2 ML25-U×2	1.39	208	386
LFWL25B MLFWL25B					250	125									1.66		
LFWL30A MLFWL30A	30		65	63	250	125	104	86	84	24	35	φ9	6	L30A-U×2 ML30-U×2	1.98	296	452
LFWL30B MLFWL30B					300	150									2.29		
LFWL35A MLFWL35A	35		72	70	250	125	112	94	90	26	40	φ9	6	L35-U×2 ML35-U×2	2.42	334	500
LFWL35B MLFWL35B					300	150									2.79		
LFWL40A MLFWL40A	40	0 -0.012	84	82	250	125	124	106	100	28	45	φ9	6	L40-U×2 ML40-U×2	3.84	560	800
LFWL40B MLFWL40B					300	150									4.36		